


SENSOR ALARM

This product adopts high sensitivity detector, integrated circuit and SMT technology; It gathers automatic, convenient, safety and practical function; The wide detection range is made of up and down, left and right service field. It utilizes human motion infrared rays as control signals, when human enter detection fields, it will start the sound system (dingdong, alarm) to call attention that person enters detection fields; It could protect you all-weather and it will give safety you never have for your family and travel ; Its using range is wide and its installation is easy.

Feature:

- The shape is cabinet; Its detection range is wide and installation is easy(It can be fastened with screw or double-faced glue);
- It has duplex function of information (dingdong) and alarm;
- It can be used indoor and travel, it can be installed level or vertical and also laid on the stable furniture.
- Its degree can be adjusted freely after installation and the range is wide



Specification:

Power source: DC 9V

Detection distance: 8m (max)

Detection range: 60°

Switch state: alarm/off/dingdong

Working temperature: -20~40℃

Working humidity: <93 %RH

Detection

motion speed: 0.6~1.5m/s

Static current: 0.15mA

Working time-delay:5s

Sense interval: about 1Min

Alarm loudness:>60db

Installation and usage:

Open both-sides of the support outward lightly, take out the sensor body


Open the battery lid on the sensor, put 9v battery on it and you could use it after 30s.

Switch function:

ALARM: turn "OFF" to "ALARM" and sense it, it will alarm immediately, the alarm time is 5s, only when sense it again after 1Min, it will alarm again.

OFF: The sensor doesn't work.

CHIME: turn "OFF" to "CHIME" and sense it, it will give 'dingdong' sound for 5s. only when sense it again after 1Min, it will give "dingdong" again.



Notes:

Please don't hit the sensor and detection windows with hard or rough object

Please don't install the sensor in the sunlight, raining and high humidity zone;

Please don't install the sensor near heat or air current changed zone;

Please take out the battery in order to avoid damaging the sensor if you don't use it for

long time; This item is not formal alarm and it has limited alarm loudness, so it can call attention to you only, but can't guarantee absolute safety. We don't undertake any responsibility if happen any unexpected event.

